

MOONS'
moving in better ways

RS Step-Servo

New

3rd Generation Step-Servo

- Closed loop step system with servo control
 - Intelligent built-in controller
 - Efficient, smooth, accurate & fast
 - Low vibration, low noise, low heat
 - Enhanced motor optimized design


**Closed
Loop**



CE **RoHS**
Compliant


The **Step-Servo** is an innovative revolution for the world of stepper motor, it enhances the stepper motors with servo technology to create a product with exceptional feature and broad capability.

Multi-functional Capability




Closed Loop

- Very tight position and velocity control for the most demanding applications.
- Robust servo loops that tolerate wide fluctuation in load inertia and frictional loading.
- Precise positioning to within $\pm 0.2^\circ$ using high resolution (4096 counts/rev) encoder.




Low Heating/High Efficiency




- Uses only the current required by the application, generating minimum heat output.
- When stand-still, current can reach nearly zero for extremely low heat output.
- Being able to use almost 100% of torque, allows for more efficient and compact motor usage.

Smooth & Accurate

- Space vector current control with 1024 line high resolution encoder, gives smooth and quiet operation, especially at low speeds. -----A feature never found with traditional stepping motors
- High stiffness due to the nature of the stepping motor combined with the highly responsive servo control -----Accurate position control both while running and static positioning




Fast Response



- When performing fast point-to-point moves, the high torque output and advanced servo control provides a very responsive system far exceeding what can be done with a conventional stepper system.


High Torque

- Because the **Step-Servo** operates in full servo mode, all the available torque of the motor can be used.
- The motor can provide as much as 50% more torque in many applications. High torque capability often eliminates the need for gear reduction.
- Boost torque capability can provide as much as 50% more torque for short, quick moves.




Motion Monitoring

- For difficult control situations where performing a precise move is necessary, the **Step-Servo Quick Tuner** provide an easy to use interface for performing and monitoring the motion profile.
- Many common parameters such as Actual Speed or Position Error can be monitored to evaluate system performance.
- The monitoring is interactive with the servo tuning capability so that optimum performance can be achieved.



Easy Tuning




- Pre-defined tuning parameters for maximum control performance and stability.
- Easy selection list provides the level of control desired.
- In most cases NO extra manual tuning is required.

Key Features

- Up to 4 digital inputs, 3 digital outputs for P/S/Q type
- AOUT+/- BOUT+/- ZOUT+/- differential encoder signal outputs for P type
- Automatic load inertia detection
- Multiple homing methods for S/Q type
- Software limit for S/Q type


Software

Step-Servo Quick Tuner



- Friendly interface
- Easy setup within just three steps
- Drive setup and configuration
- Servo tuning and sampling
- Motion testing and monitoring
- Write and save SCL command scripts
- Integrated online help

Built-in Q Programming




- Single-axis motion control
- Stored program execution
- Multi-tasking
- Conditional processing
- Math functions
- Data registers
- Motion profile simulation
- Online help integrated

FREE DOWNLOAD

Our software and user manual can be downloaded from our website:
www.moonsindustries.com

All software applications run on Windows 7, Windows 8, 32-bit or 64-bit, Windows XP.

■ System Configuration




◇ -P Software Setting Pulse Input Type

Controlled via pulse generator.

Main Features

- Accepts three types of pulse signal input as Pulse&Direction, CW/CCW and A/B Quadrature
- Encoder Outputs




◇ -S Basic Type with Serial Communication

Controlled via pulse signals, or MOONS' SCL streaming series commands.

Main Features

- Pulse control
- Host real time control using SCL via RS-232



◇ **-Q Built-in Programmable Motion Controller**

Run stand-alone with sophisticated and functional programs. Commands for controlling motion, inputs & outputs, drive configuration and status, as well as math operations, register manipulation, and multi-tasking.

Main Features

- Stand-alone operation plus Serial host control
- Math operations
- Register manipulation
- Multi-tasking
- With all features in S type

■ **Drive Specifications**


Power Amplifier	
Amplifier Type	Dual H-Bridge, 4 Quadrant
Current Control	4 state PWM at 20 KHz
Output Current	RS03: Continuous Current 3A max, Boost Current 4.0A max (1.5s), current limitation auto set-up by attached motor RS06: Continuous Current 6A max, Boost Current 7.5A max (1.5s), current limitation auto set-up by attached motor RS10: Continuous Current 10A max, Boost Current 12A max (1.5s), current limitation auto set-up by attached motor
Power Supply	External nominal 24 - 70 volt DC power supply required, Absolute maximum input voltage range 18 - 75 VDC
Protection	Over-voltage, under-voltage, over-temp, motor/winding shorts (phase-to-phase, phase-to-ground)
Controller	
Electronic Gearing	Software selectable from 200 to 51200 steps/rev in increments of 2 steps/rev
Filters	Digital input noise filter, Smoothing filter, PID filter, Notch filter
Non-Volatile Storage	Configurations are saved in FLASH memory on-board the DSP
Modes of Operation	P type: Position Mode(Pulse & Direction, CW & CCW Pulse, A/B Quadrature) S type: Position Mode(Pulse & Direction, CW & CCW Pulse, A/B Quadrature); Torque Mode, Velocity Mode, SCL Mode Q type: Position Mode(Pulse & Direction, CW & CCW Pulse, A/B Quadrature); Torque Mode, Velocity Mode, SCL Mode, Q Programming
Digital Inputs	P/S/Q type: X1/STEP, X2/DIR, Optically isolated, differential, 5-24VDC; Minimum pulse width = 250 ns, Maximum pulse frequency = 2 MHz; X3,X4:optically isolated, single-ended, sinking or sourcing, 5-24VDC, minimum pulse width 50µs, maximum pulse frequency 10KHz;
Digital Outputs	P/S/Q type: Y1/Alarm, Y2/In Position, Y3/Brake; Optically isolated, 30V/100 mA max
Encoder Outputs	P type: Differential encoder outputs (AOUT+/- BOUT+/- ZOUT+/-), 26C31 line driver, 20 mA sink or source max
Communication	RS-232
Physical	
Ambient Temperature	0 to 40°C (32 to 104°F) when mounted to a suitable heatsink
Ambient Humidity	90% Max., non-condensing
Mass	Approx 0.2 Kg

Dimensions

Visit www.moonsindustries.com to get the 3D drawings.


Motor (Unit:mm)

AM11RS




Model	L
AM11RS1DMA	43.8
AM11RS2DMA	52.9
AM11RS3DMA	64.1

AM17RS




Model	A	A1	B	B1	L
AM17RS1DMA	φ 6	5.5	20	15	59.5
AM17RS1DMB	φ 5	4.5	24	15	59.5
AM17RS2DMA	φ 6	5.5	20	15	65
AM17RS2DMB	φ 5	4.5	24	15	65
AM17RS3DMA	φ 6	5.5	20	15	73.5
AM17RS3DMB	φ 5	4.5	24	15	73.5
AM17RS4DMA	φ 6	5.5	20	15	89
AM17RS4DMB	φ 5	4.5	24	15	89

AM23RS




Model	A	A1	B	B1	L
AM23RS2DMA	φ 8	7.5	24	20	77.5
AM23RS2DMB	φ 6.35	5.85	20	15	77.5
AM23RS3DMA	φ 8	7.5	24	20	99.5
AM23RS3DMB	φ 6.35	5.85	20	15	99.5
AM23RS4DMA	φ 8	7.5	24	20	102.5

AM24RS



Model	A	A1	B	B1	L
AM24RS3DMA	φ 10	9.5	24	20	110
AM24RS3DMB	φ 8	7.5	20.6	15	110


AM34RS



Model	L
AM34RS1DMA	88
AM34RS3DMA	117.5
AM34RS5DMA	147


◇ Drive (Unit:mm)

RS03/06/10-P



Part Number		
RS03-P-A	RS06-P-A	RS10-P-A


RS03/06/10-S/Q



Part Number					
RS03-S-A	RS06-S-A	RS10-S-A	RS03-Q-A	RS06-Q-A	RS10-Q-A

Motor Specifications


Motor P/N	Drive P/N	Torque	Rotor Inertia	Encoder Resolution	Maximum Speed	Mass	Frame Size	Permissible Overhung Load (N) Distance(L) from Shaft End(mm)					Permissible Thrust Load
		N•m	g•cm ²	counts/rev	RPM			0	5	10	15	20	
AM11RS1DMA	RS03-■-A	0.065	9	4096	3000	118	28	20	25	34	52	-	Less than the motor mass
AM11RS2DMA		0.08	12			168							
AM11RS3DMA		0.125	18			218							
AM17RS1DM □		0.26	38			390	42	35	44	58	85	-	
AM17RS2DM □		0.42	57			440							
AM17RS3DM □		0.52	82			520							
AM17RS4DM □	0.7	123	760			56	63	75	95	130	190		
AM23RS2DM □	0.95	260	850										
AM23RS3DM □	1.5	460	1250										
AM23RS4DMA	2.4	365	1090			60	90	100	130	180	270		
AM24RS3DM □	2.5	900	1650										
AM34RS1DMA	RS10-■-A	2.7	915			2000	80	260	290	340	390	480	
AM34RS3DMA		5.2	1480	3100									
AM34RS5DMA		7.0	2200	4200									




□: A or B, refer to motor part numbering system; ■: P, S or Q refer to driver part numbering system;

Torque Curves


AM11RS Series




AM17RS Series




AM23RS Series



AM34RS Series



■ **Numbering System**



■ **Ordering Information**

Control	Drive Type	Motor Type	Torque
P Type Pulse Input Type RS-232 Communication 4 Digital Inputs 3 Digital Outputs Encoder Outputs	RS03-P-A	AM11RS1DMA	0.065N·m
		AM11RS2DMA	0.08N·m
		AM11RS3DMA	0.125N·m
		AM17RS1DM □	0.26N·m
		AM17RS2DM □	0.42N·m
		AM17RS3DM □	0.52N·m
	RS06-P-A	AM17RS4DM □	0.7N·m
		AM23RS2DM □	0.95N·m
		AM23RS3DM □	1.5N·m
		AM23RS4DMA	2.4N·m
	RS10-P-A	AM24RS3DM □	2.5N·m
		AM34RS1DMA	2.7N·m
AM34RS3DMA		5.2N·m	
		AM34RS5DMA	7.0N·m

Control	Drive Type	Motor Type	Torque
S Type Basic Type RS-232 Communication 4 Digital Inputs 3 Digital Outputs	RS03-S-A	AM11RS1DMA	0.065N·m
		AM11RS2DMA	0.08N·m
		AM11RS3DMA	0.125N·m
		AM17RS1DM □	0.26N·m
		AM17RS2DM □	0.42N·m
		AM17RS3DM □	0.52N·m
	RS06-S-A	AM17RS4DM □	0.7N·m
		AM23RS2DM □	0.95N·m
		AM23RS3DM □	1.5N·m
		AM23RS4DMA	2.4N·m
	RS10-S-A	AM24RS3DM □	2.5N·m
		AM34RS1DMA	2.7N·m
		AM34RS3DMA	5.2N·m
		AM34RS5DMA	7.0N·m

Control	Drive Type	Motor Type	Torque
Q Type Programm Type RS-232 Communication 4 Digital Inputs 3 Digital Outputs	RS03-Q-A	AM11RS1DMA	0.065N·m
		AM11RS2DMA	0.08N·m
		AM11RS3DMA	0.125N·m
		AM17RS1DM □	0.26N·m
		AM17RS2DM □	0.42N·m
		AM17RS3DM □	0.52N·m
		AM17RS4DM □	0.7N·m
	RS06-Q-A	AM23RS2DM □	0.95N·m
		AM23RS3DM □	1.5N·m
		AM23RS4DMA	2.4N·m
		AM24RS3DM □	2.5N·m
	RS10-Q-A	AM34RS1DMA	2.7N·m
		AM34RS3DMA	5.2N·m
		AM34RS5DMA	7.0N·m

□: Enter A(Enhanced Shaft) or B(Standard) in the box(□) within the model name

■ Standard Accessories (Within the package)

P/N	Category	Technical Specification
1103-200	Cable	Power Supply Cable
2101-150	Cable	RS-232 Communication Cable

■ Optional Accessories (Sold separately)


P/N	Category	Technical Specification
RC880	Regeneration Clamp	80VDC Max. 50W
MS-USB-RS-232-01	USB Converter	USB-RS-232
1108-□□□	Cable	RS-S/Q Standard I/O Cable, Shield
1115-□□□	Cable	RS-P Standard I/O Cable, Shield
2103-□□□	Cable	Motor Extension Cable for AM17/23/24/34RS motor
2109-□□□	Cable	Motor Extension Cable for AM11RS motor
2116-□□□	Cable	Encoder Extension Cable for AM17/23/24/34RS motor
2118-□□□	Cable	Encoder Extension Cable for AM11RS motor

◇ Regeneration Clamp (Unit:mm)

P/N: RC880

When using regulated power supply you may encounter a problem with regeneration. The kinetic energy caused by regeneration is transferred back to the power supply. This can trip the overvoltage protection of a switching power supply, causing it to shut down.

MOONS' offer the RC880 "regeneration clamp" to solve this problem. If in doubt, use an RC880 for your first installation. If the "regen" LED on the RC880 never flashes, you don't need the clamp.




◇ USB Converter

Model: MS-USB-RS-232-01
 Description: USB-RS-232 converter




◇ Motor Extension Cable for AM11RS motor



P/N	Length (L)
2109-100	1M
2109-300	3M
2109-500	5M
2109-1000	10M

Wiring Diagram		
PIN (J1)	Colour(Signal)	PIN (J2)
1	Blue (B-)	1
3	Red (B+)	2
4	Green (A-)	3
6	Black (A+)	4


◇ Motor Extension Cable for AM17/23/24/34RS motor



P/N	Length (L)
2103-100	1M
2103-300	3M
2103-500	5M
2103-1000	10M

Wiring Diagram		
PIN (J1)	Colour(Signal)	PIN (J2)
1	Blue (B-)	1
2	Red (B+)	2
3	Green (A-)	3
4	Black (A+)	4


◇ Encoder Extension Cable for AM11RS motor



P/N	Length (L)
2118-100	1M
2118-300	3M
2118-500	5M
2118-1000	10M

Wiring Diagram						
PIN (J1)	Colour(Signal)	PIN (J2)	PIN (J1)	Colour(Signal)	PIN (J2)	
10	Blue (A+)	1		Brown (U+)		
9	Blue/Black (A-)	2		Brown/Black (U-)		
8	Green (B+)	3		Gray (V+)		
7	Green/Black (B-)	4		Gray/Black (V-)		
6	Yellow (Z+)	5	1	White (W+)	15	
5	Yellow/Black (Z-)	6	2	White/Black (W-)	16	
3	Red (+5V)	7	12	Shield	10	
4	Black (GND)	8				


◇ Encoder Extension Cable for AM17/23/24/34RS motor



P/N	Length (L)
2116-100	1M
2116-300	3M
2116-500	5M
2116-1000	10M


Wiring Diagram						
PIN (J1)	Colour(Signal)	PIN (J2)	PIN (J1)	Colour(Signal)	PIN (J2)	
A6	Blue (A+)	1		Brown (U+)		
B6	Blue/Black (A-)	2		Brown/Black (U-)		
A5	Green (B+)	3		Gray (V+)		
B5	Green/Black (B-)	4		Gray/Black (V-)		
A4	Yellow (Z+)	5	A2	White (W+)	15	
B4	Yellow/Black (Z-)	6	B2	White/Black (W-)	16	
A3	Red (+5V)	7	A1	Shield	10	
B3	Black (GND)	8				

◇ Standard I/O Cable (For RS03/06/10-S/Q)



P/N	Length (L)	Wiring Diagram			
		PIN (J1)	Colour(Signal)	PIN (J1)	Colour(Signal)
1108-030	30CM	1	Blue (STEP+)	8	Black (XCOM)
1108-100	1M	2	Blue/Black (STEP-)	9	Brown (Y1+)
1108-200	2M	3	Green (DIR+)	10	Brown/Black (Y1-)
		4	Green/Black (DIR-)	11	Gray (Y2+)
		5	Yellow (X3/EN)	12	Gray/Black (Y2-)
		6	Yellow/Black (X4/AR)	13	White (Y3+)
		7	Shield	14	White/Black (Y3-)

◇ Standard I/O Cable (For RS03/06/10-P)



P/N	Length (L)	Wiring Diagram			
		PIN (J1)	Colour(Signal)	PIN (J1)	Colour(Signal)
1115-030	30CM	1	Blue/White (STEP+)	12	Gray/Black (Y2-)
1115-100	1M	2	Blue/Black (STEP-)	13	Purple/White (Y3+)
1115-200	2M	3	Green/White (DIR+)	14	Purple/Black (Y3-)
		4	Green/Black (DIR-)	15	NC
		5	Purple (X3)	16	Black (GND)
		6	Blue (X4)	17	Red/White (AOUT+)
		7	Shield	18	Red/Black (AOUT-)
		8	Brown (XCOM)	19	Orange/White (BOUT+)
		9	Brown/White (Y1+)	20	Orange/Black (BOUT-)
		10	Brown/Black (Y1-)	21	Yellow/White (ZOUT+)
		11	Gray/White (Y2+)	22	Yellow/Black (ZOUT-)

Customer Service Center



400-820-9661

■ MOONS' Headquarter

168 Mingjia Road, Minhang District, Shanghai
201107, P.R. China

■ Domestic Offices

Shenzhen

Room 503, Building A7, Nanshan iPark, No.1001, Xueyuan Ave,
Nanshan Dist, Shenzhen 518071, P.R. China

Beijing

Room 1206, Jing Liang Mansion, No.16 Middle Road of East,
3rd Ring, Chaoyang District, Beijing 100022, P.R. China

Nanjing

Room 1101-1102, Building 2, New Town Development
Center, No.126 Tianyuan Road, Moling Street,
Jiangning District, Nanjing 211106, P.R. China

Qingdao

Room 1710, Zhuoyue Tower, No.16 Fengcheng Road,
Shibei District, Qingdao 266000 P.R. China

Wuhan

Room 3001, World Trade Tower, 686 Jiefang Avenue,
Jiangnan District, Wuhan 430022, P.R. China

Chengdu

Rm. 3907, Maoye Plaza, No.19, Dongyu Street,
Jinjiang District, Chengdu 610066, P.R. China

Xi'an

Room 1006, Tower D, Wangzuo International City,
1 Tangyan Road, Xi'an 710065, P.R. China

Ningbo

Room 309, Tower B, Taifu Plaza, 565 Jiangjia Road,
Jiangdong District, Ningbo, 315040, P.R. China

Guangzhou

Room 4006, Tower B, China Shine Plaza, 9 Linhe Xi Road,
Tianhe District, Guangzhou 510610, P.R. China

Chongqing

Rm. 2108, South yuanzhu Buliding 20, No.18 Fuquan Rd.,
Jiangbei District, Chongqing 400000, P.R. China

■ North America Company

MOONS' INDUSTRIES (AMERICA), INC. (Chicago)
1113 North Prospect Avenue, Itasca, IL 60143 USA

MOONS' INDUSTRIES (AMERICA), INC. (Boston)
36 Cordage Park Circle, Suite 310 Plymouth, MA 02360 USA

APPLIED MOTION PRODUCTS, INC.
404 Westridge Dr. Watsonville, CA 95076 USA

LIN ENGINEERING, INC.
16245 Vineyard Blvd., Morgan Hill, CA 95037 USA

■ European Company

MOONS' INDUSTRIES (EUROPE) S.R.L.
Via Torri Bianche n.1 20871 Vimercate(MB) Italy

AMP & MOONS' AUTOMATION (GERMANY) GMBH
Borsenstrabe 14
60313 Frankfurt am Main Germany

■ South-East ASIA Company

MOONS' INDUSTRIES (SOUTH-EAST ASIA) PTE. LTD.
33 Ubi Avenue 3 #08-23 Vertex Singapore 408868

■ Japan Company

MOONS' INDUSTRIES JAPAN CO., LTD.
Room 602, 6F, Shin Yokohama Koushin Building,
2-12-1, Shin-Yokohama, Kohoku-ku, Yokohama,
Kanagawa, 222-0033, Janpan



<http://www.moons.com.cn>

E-mail: ama-info@moons.com.cn

MOONS'
moving in better ways

- All the specifications, technical parameters of the products provided in this catalog are for reference only, subject to change without notice. For the latest details, please contact our sales department.